



SPA 3806
10 Zone Speaker Selector

Siera manufactures reliable and affordable solutions in Electronic Security, CCTV, Access Control, Intercommunications, Professional Audio and Automation.

Featured specifications

- 10 Zone Speaker Selector
- Expandable to 200 zone
- Capacity to divide one amplifier into 10 zones
- Each 10 zone with working indicator and selective buttons
- With fire alarm interface
- With all zone on/off button for easy operation.
- 4 line inputs and 4 EMC inputs, built-in 5W monitor speaker
- Black finish of aluminum front panel
- 19" rack mount type with mounting handheld
- 3 years warranty

Group A Input:	70V/100V, Aux Signal
Group B Input:	70V/100V, EMC and Aux Signal
Zone:	CH1~CH10
Power Load:	Total: 1KW; Each zone: 100 W
Channel Exchange:	500W, Aux Signal
Contact Input:	(0V) short circuit contact input,(ALARM IN)
Contact Output:	(0V) short circuit contact two output (ALARM OUT)
Wire Cable:	(3×0.75 mm ²)×1.5 meters
Power Supply:	AC 110V / 220V - 50-60Hz
Power Consumption:	10~15W
Dimension:	483(W)×350(D) × 89(H) mm
Net weight:	6.4kg
Gross weight:	8.1kg

